

# SISTEMAS DE CIERRE ELECTRÓNICO ELECTRONIC LOCKING SYSTEMS

### Gateway

It is an essential key for facilities with wireless locker locks, since it works as a link in the communications between wireless locks and iVIEW software for lockers.

WE MAKE SENSE ENKOA




## GATEWAY




#### **Characteristics**

Gateway
PLCxK3P4
Universal (85-264VAC)
4 opto- isolated inputs for potential free relays or external direct tension inputs of 5vdc-24vdc
5vdc
Solid red when turning on and multicolor led for different functions.
EEPROM external storage memory of 256 kbytes
LCD, alphanumeric of 16 characters x 2 lines
4 key matrix attached to the box.
RS232, MODBEE( IEEE802.15.4) and Ethernet.
Real time, 24 h autonomy in case of electric power cuts.
At the PCB for option configurations
208 (Height)x 158 (Width) X 83,5(Depth) mm / 660 grs.

#### **Dimensions**





#### **Benefits**

MAX.ELEMENTS: It manages up to 175 locker locks.

HIGH DISTANCE COVERAGE: It covers an area extension of 40-50 metres.

OUTDOORS. It is suitable for outdoors / indoors.

**KEYBOARD**. It has a keyboard for basic parameter configuration.



Enkoa System S.L.

